

ATTORNEY DOCKET NO.
PA060013

PATENT APPLICATION
Express Mail No. ER 021245352 US

1

A BIDIRECTIONAL ROUTER AND A METHOD
OF BIDIRECTIONAL AMPLIFICATION

TECHNICAL FIELD OF THE INVENTION

The invention relates to a router and to a method of monodirectional amplification of bidirectional optical signals.

BACKGROUND OF THE INVENTION

5 In optical transmission systems it is frequently desired to use an optical fibre for bidirectional communication. This is achieved in most practical systems by using wavelength multiplexing so that transmission in one direction takes place at one or more wavelengths, and so that transmission in the other direction takes place at one or more other wavelengths different from the first-mentioned wavelengths.

10 Since the signals are transmitted through an optical fibre, they will be subjected to attenuation, which necessitates amplification of the optical signals if they are to be transmitted over great distances.

15 According to the prior art this bidirectional amplification may be achieved by suitable coupling of wavelength multiplex couplers and a unidirectional amplifier. This method, however, is complicated and consequently involves relatively huge costs.

SUMMARY OF THE INVENTION

When, as stated in claim 1, the router comprises two optical couplers interconnected serially via a delay device and wherein the optical router further comprises an optical amplifier optically connected to one of the optical couplers, a simple and economical router obtained, which may be designed according to simple dimensioning principles and be adapted to concrete applications. The property that for each optical input an optical coupler ideally divides an arriving optical signal between the outputs of the coupler means that an output signal from the first coupler contains mixed signals, which may subsequently be "mixed back" in the following optical coupler. In a suitable embodiment of the delay device, this back-mixing may have the effect that signals with different wavelength components may be fed jointly and selectively to a selected output port on the following coupler, ideally, with conservation of energy, as the interferometer properties of the delay device are utilized.

This complete signal may additionally be fed back into a port on the following coupler, whereby the input ports of the first coupler also serve as output ports.

This property is particularly advantageous in applications where a bidirectional optical signal is to be amplified with a monodirectional amplifier, as a monodirectional amplifier may be coupled between the terminals of the last coupler and amplify both optical signals, following which these, in an amplified state, may be fed back to the bidirectional port of the router. It is noted in particular that the amplified signal is routed to another bidirectional port, for which reason the complete router may be coupled between two fibre ends

of a directional light guide cable having a fibre end for
bidirectional router ports, amplify arriving optical
signals with given wavelengths, and transmit these out on
the other bidirectional port to the other fibre end and
5 further on the light guide in the same direction as when
arrived at the router.

When, as stated in claim 2, the delay device
comprises a difference in distance ΔL between the two
optical guides connecting the two couplers, a simple
10 embodiment of the invention is obtained, as the
difference in distance ΔL provides a mutual phase shift
between the two optical signals on the input of the
following coupler, which means that the coupler serves as
an interferometer in the mixing in the coupler itself.

15 It will be appreciated that ΔL is not to be taken to
mean a separate physical element, but is an indication of
the real MZI difference in distance between the two
serially connected couplers.

When, as stated in claim 3, 3 dB couplers are used,
20 a particularly simple embodiment of the invention is
obtained. The use of 3 dB couplers will usually be
preferred, as the characteristic of the complete router
is particularly simple when the optical branches of the
constituent couplers are symmetrical.

25 When, as stated in claim 4, the delay device is
formed by one or more pairs of electrodes arranged along
the optical path, a further embodiment of the invention
is obtained, wherein a desired phase shift between the
optical signals may be achieved by changing the
30 refractive index in the optical path in the delay element
in response to an electrical field applied by the
electrodes.

When, as stated in claim 5, the delay element is provided with one or more pairs of electrodes arranged along the optical path in the delay element to achieve a supplementary time delay, an advantageous embodiment of the invention is obtained, as a desired phase shift between the optical signals may be obtained at an optical difference in distance ΔL , and be finely adjusted by changing the refractive index in the optical path in the delay element in response to an electrical field applied by the electrodes.

When, as stated in claim 6, ΔL is equal to $\lambda^2/(2\Delta\lambda n)$ where λ indicates the optical wavelength used, n is the refractive index, and $\Delta\lambda$ indicates the half-period of the power transfer function, i. e. $\frac{1}{2}\text{FSR}$ (FSR = free spectral range), a practical embodiment of the invention is obtained.

For clarity, it should be mentioned that a selected wavelength of 1550 nm, a refractive index $n = 1.5$, and $\Delta\lambda = 10\text{nm}$, result in a difference in distance of $\Delta L = 80\ \mu\text{m}$.

When, as stated in claim 7, the router is made in an integrated design, an optimum design for commercial use obtained. This should be taken to mean that the actual design of the delay element is to be made with a relatively great precision, as the necessary distances ΔL are relatively small, and even small deviations therefrom give rise to a relatively great unreliability with respect to the overall system.

When, as stated in claim 8, the optical signals in each direction toward the router are fed to the first bidirectional port A and the second bidirectional port D, respectively, of the router and from there to the first

unidirectional port B of the router, further through an optical amplifier connected to the unidirectional ports and from there through the second unidirectional port C of the router and back through the router to the second
5 bidirectional D and the first bidirectional port A, respectively, an effective bidirectional amplification is obtained, using relatively inexpensive elements. The bidirectional amplification obtained is moreover obtained using just one monodirectional amplifier.

10 When, as stated in claim 9, λ_{r1} and λ_{r2} are allocated on the power transfer function of the router in one transmission direction on each side of a maximum of λ_R , and λ_{l1} and λ_{l2} are allocated on the power transfer
15 function of the router in the other transmission direction on each side of a maximum of λ_L , said bidirectional optical signals having the wavelengths λ_{l1} and λ_{l2} in one direction and having the wavelengths λ_{r1} and λ_{r2} in the other direction, said λ_L and λ_R indicating
20 a maximum in a specific frequency band for the power transfer function of the router in one direction and the power transfer function of the router in the other direction, respectively, an effective amplification of a bidirectional signal is obtained, using a relatively
25 simple and inexpensive technique, as a two-channel signal may thus be transmitted and amplified each way through the router.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention will be described below with reference to the drawing, in which:

5 FIGURE 1 shows a communications system consisting of network elements;

FIGURE 2 shows an MZI router according to the invention;

FIGURE 3 shows a known coupler;

10 FIGURE 4 shows a preferred embodiment of the invention;

FIGURE 5 shows a first channel coupling characteristic an MZI router of the invention; and

FIGURE 6 shows an additional channel coupling characteristic for an MZI router of the invention.

15

DETAILED DESCRIPTION OF THE INVENTION

FIGURE 1 shows a communications system consisting of two network elements 1 and 2 connected by a wavelength multiplexed bidirectional optical connection 3. The network element 2 transmits at the wavelength λ_L , and the network element 1 transmits at the wavelength λ_R . Since the connection is wavelength-divided, it is possible to transmit communications signals from 1 to 2 while transmitting from 2 to 1. In practical systems, the connection 3 is an optical fibre which subjects the transmitted signals from both 1 and 2 to attenuation through the fibre. If the system is to be used over great distances, it is necessary to insert one or more amplifiers in the connection 3.

If there is one or more locations on the connection 3 where the signals, which are transmitted from both 1 and 2, have travelled such a great distance through the optical fibre as makes it necessary to amplify them, then a router is inserted so that a single traditional unidirectional amplifier may be used transmitted from both 1 and 2. for amplifying signals transmitted from both 1 and 2.

FIGURE 2 shows a known router 10.

The router 10 has two bidirectional ports 5 and 6 and two unidirectional ports 7 and 8. An amplifier 9 is inserted between the two unidirectional ports 7 and 8. The input of the amplifier is connected to the unidirectional port 7, and the output of the amplifier is connected to the unidirectional port 8.

On the ports 5 and 6, the router 10 is connected to two optical fibres 3' and 3" which are connected to the ports 5 and 6, respectively.

The router 10 is arranged such that a signal transmitted at the wavelength λ_L into the router through the port 5 has maximum power on the port 7 and minimum power on the port 8. Correspondingly, a signal
5 transmitted at the wavelength λ_R into the router through the port 6 has maximum power on the port 7 and minimum power on the port 8. The amplifier may therefore amplify the signals at both λ_R and λ_L . The amplified signals are transmitted via the same router 10 through the port 8.
10 The amplified signal at λ_R is transmitted out through the port 5, and, correspondingly, the amplified signal at λ_L is transmitted out through the port 6. Such a router 10 thus ensures that a traditional unidirectional amplifier may be used for amplifying bidirectional signals.

15 In the figure, a unidirectional amplifier 9 is connected to the unidirectional output port 9 of the router 10 and the unidirectional input port 8 of the router 10.

FIGURE 3 shows how a known router 10 is constructed.

20 The router comprises four wavelength multiplex couplers 15, 16, 17 and 18. The wavelength multiplex couplers are also called WDM couplers.

The wavelength multiplex coupler 15 is connected to the wavelength multiplex coupler 17 via an optical
25 connection 11. The wavelength multiplex coupler 16 is connected to the same wavelength multiplex coupler 17 via an optical connection 12. The wavelength multiplex coupler 17 subsequently optically connected to the port 7.

30 The wavelength multiplex coupler 15 filters such that the optical signal λ_L , received on the port 5 via the connection 11, is fed to the wavelength multiplex

coupler 17, while the wavelength multiplex coupler 16 filters such that the optical signal λ_r , received on the port 6 via the connection 12, is fed to the wavelength multiplex coupler 17. The complete signal consisting of
5 λ_r and λ_l is thus fed to the port 7, which may subsequently be connected to an optical amplifier capable of amplifying the complete received signal from the fibre 3' and 3", respectively.

Subsequently, an input port 8 feeds the complete
10 amplified signal to the wavelength multiplex coupler 18, which separates the received amplified optical signal again into two amplified signals consisting of λ_r and λ_l , respectively, which are fed via the connections 14 and 13 to the wavelength multiplex coupler 15 and the wavelength
15 multiplex coupler 16, respectively, which subsequently feed the amplified signals at λ_r and λ_l , respectively, out to the ports 5 and 6 connected to them.

FIGURE 4 shows a preferred embodiment of the invention.

20 The shown router 10 of the invention comprises two 3 dB couplers 21 and 22.

The coupler 21 comprises ports A, A', D and D', and the coupler 22 comprises ports B', B, C' and C.

The ports A' and B' are interconnected optically,
25 and also the ports D' and C' are interconnected optically.

The central aspect of the invention is the transmission matrix T of the optical 3 dB coupler. With reference to FIGURE 4 an optical field $\bar{E}_1(\lambda_1)$ at the
30 wavelength λ_1 applied to the port A and a second field $\bar{E}_2(\lambda_2)$ at the wavelength λ_2 applied to the port D of an

ideal 3 dB coupler will give rise to an optical field on the port A', D'.

$$\begin{bmatrix} \bar{E}_{A'} \\ \bar{E}_{D'} \end{bmatrix} = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & e^{j\frac{\pi}{2}} \\ e^{j\frac{\pi}{2}} & 1 \end{bmatrix} \begin{bmatrix} \bar{E}_1(\lambda_1) \\ \bar{E}_2(\lambda_2) \end{bmatrix}$$

where the transmission matrix T_1 of the 3 dB coupler is defined:

$$T_1 = \begin{bmatrix} 1 & e^{j\frac{\pi}{2}} \\ e^{j\frac{\pi}{2}} & 1 \end{bmatrix}$$

Without loss of generality, losses in the transmission A' to B' and D' to C' and the absolute time delay in the transmission may be disregarded. The only important parameter in the transmission is therefore the difference in distance Δ_L between the two optical connections A' to B' and D' to C'. The transmission matrix T_2 for the four-port A', B', C', D' may be written:

$$T_2 = \begin{bmatrix} e^{-j\frac{2\pi}{\lambda}n\Delta L} & 0 \\ 0 & 1 \end{bmatrix}$$

Since B', C' in fig. 4 are connected to another ideal 3 dB coupler, the transmission matrix T_3 for the port B', C', B, C is known, since $T_3 = T_1$. The overall transmission matrix T_s for the port A, D, B, C may be written

$$T_s = T_3 T_2 T_1$$

and the fields on the ports B and C may thereby be calculated

$$\begin{bmatrix} \bar{E}_B \\ \bar{E}_C \end{bmatrix} = \left(\frac{1}{\sqrt{2}} \right)^2 \begin{bmatrix} 1 & e^{j\frac{\pi}{2}} \\ e^{j\frac{\pi}{2}} & 1 \end{bmatrix} \begin{bmatrix} e^{-j\frac{2\pi}{\lambda}n\Delta L} & 0 \\ 0 & 1 \end{bmatrix} \begin{bmatrix} 1 & e^{j\frac{\pi}{2}} \\ e^{j\frac{\pi}{2}} & 1 \end{bmatrix} \begin{bmatrix} \bar{E}_1(\lambda_1) \\ \bar{E}_2(\lambda_2) \end{bmatrix}$$

Owing to the symmetry of the optical circuit, the transmission matrix T_s may also be used for calculating the fields which will occur on the ports A and D as a

function of the fields applied to the ports B and C, i.e. the opposite way back through the router. It is noted that, ideally, no field is applied to B but just to the port C according to the invention.

5 As another object of the invention is the extinction of the field on the port C caused by the fields on the port A and D, the conditions of this extinction are made in the light of the transmission matrix T_s

$$\bar{E}_c = \bar{E}_1(\lambda_1) \left(e^{-j\frac{2\pi}{\lambda_1}n\Delta L} + e^{j\pi} \right) + \bar{E}_2(\lambda_2) \left(e^{-j\frac{2\pi}{\lambda_1}n\Delta L} + e^{j\pi} \right)$$

10 For this field to be extinguished, the coefficients of $\bar{E}_1(\lambda_1)$ and $\bar{E}_2(\lambda_2)$ must be zero. This is satisfied if ΔL is selected so that

$$\frac{2\pi}{\lambda_1}n\Delta L = p2\pi$$

and

15
$$\frac{2\pi}{\lambda_2}n\Delta L = p2\pi + \pi$$

where $p \in N$, the set of natural numbers.

Similar calculations give the resulting field on the port B:

$$\bar{E}_B = -\bar{E}_1(\lambda_1) + \bar{E}_2(\lambda_2)$$

20 This means that the fields $\bar{E}_1(\lambda_1) + \bar{E}_2(\lambda_2)$ are transmitted out of the port B with full amplitude, and that the fields will be extinct on the port C, thereby allowing a unidirectional amplifier to be used between the terminals B and C.

25 If the field E_B is amplified and coupled on the port C, the transmission matrix T_s may be used for calculating the field which occurs on the port A and D as a consequence of the amplified field on the port C. The fields on the ports A and D caused by the field applied

to the port C are calculated relatively to the field on the port C:

The field into the port C is defined:

$$\bar{E}_C = -\bar{E}_1(\lambda_1) + \bar{E}_2(\lambda_2)$$

5 and results in a field on the port

$$\bar{E}_A = -\bar{E}_2(\lambda_2)e^{j\frac{\pi}{2}}$$

Similarly, the field out of the port D is calculated:

$$\bar{E}_D = -\bar{E}_1(\lambda_1)$$

10 This means that the field received e.g. on the port A at the wavelength λ_B may be amplified and transmitted out of the port D, and a field received on the port D at the wavelength λ_R may be amplified with the same amplifier and transmitted out of the port A.

15 A power consideration illustrates how an MZI router may directionally couple several channels at various wavelengths in each direction. This is possible, provided that complete extinction of the fields on the port C is not necessary. This may be achieved
20 particularly when optical insulators are used in connection with the two terminals of the optical amplifier.

If it is defined that $\bar{E}_2(\lambda_2) = \bar{0}$ on the port D and $\bar{E}_1(\lambda_1)$ on the port A have the power P_1 , the resulting power
25 and P_B and P_C on the port B and the port C, respectively, may be calculated

$$P_B = \frac{1}{2}P_1 \left(1 + \cos \left(\frac{2\pi f}{c} n \Delta L + \pi \right) \right)$$

and

$$P_C = \frac{1}{2}P_1 \left(1 + \cos \left(\frac{2\pi f}{c} n \Delta L \right) \right)$$

where frequency is substituted for wavelength. It will be seen that the two power transfer functions are offset with respect to each other and are period with the period $\Delta f = \text{FSR}$, the free spectral range

5
$$\text{FSR} = \frac{c}{n\Delta L}$$

FIGURE 5 shows a first channel coupling characteristic for an MZI router. The figure shows a first example of how two frequency multiplexed channels in each direction may be allocated in relation to the power transfer function. The power transfer function of the MZI router has two minima/maxima in a specific frequency band at λ_R and λ_L , respectively. The four channels are positioned two by two in terms of frequency so that the two wavelengths λ_{r1} and λ_{r2} associated with λ_R are positioned on each side of minima/maxima λ_R and so that the two wavelengths λ_{l1} and λ_{l2} associated with λ_L are positioned on each side of minima/maxima λ_L . It is noted that the shown allocation windows $\Delta r1$, $\Delta r2$ and $\Delta l1$, $\Delta l2$ indicate the wavelengths which may be selected for each of the above-mentioned four channels λ_{r1} , λ_{r2} , λ_{l1} and λ_{l2} .

In the shown embodiment, one boundary of the allocation window is selected in consideration of the fact that the difference between the transmission of the power transfer function from A to D and vice versa must be at least 10 dB. It is noted that this boundary may vary from application to application.

The other boundary of each allocation window is selected in consideration of the fact that there should be a certain minimal spacing between the channels on each

side of λ_R and A_L , respectively, since there is a certain tolerance on the laser sources used for each channel.

FIGURE 6 shows another channel coupling characteristic for an MZI router. The figure shows
5 another example of how two channels in each direction may be allocated in relation to the power transfer function. The power transfer function of the MZI router has four minima/maxima in a specific frequency band in which the four channels are positioned.

10 The allocation windows Δr_1 , Δr_2 and Δl_1 , Δl_2 may be selected in this case separately in consideration of the fact that the difference between the transmission of the power transfer function from A to D and vice versa must be at least 10 dB. It should be noted that this limit
15 may vary from application to application.